

LED IN-GROUND LIGHT INSTALLATION GUIDE

Eurolumen

MODEL ELA702

MODEL-SPECIFIC BURIAL SLEEVE SYSTEM

1

VERIFY ELA702 / D55 FACE / MATCHING BURIAL SLEEVE

2

MARK D45 SLEEVE POSITION / PROVIDE DRAINAGE

3

SET D45 x H70 mm SLEEVE FLUSH AND LEVEL

4

JOIN IP-RATED CONNECTOR / LOCK / SEAL


5

COMPRESS SIDE RETAINERS / LOWER FIXTURE / CONFIRM FLUSH SEAT

6

POWER ON / COMMISSION / CHECK OUTPUT, SEAL AND DRAINAGE

ELA702 POWER / CONTROL CONNECTION



MATCH SUPPLY, POLARITY, WIRE COUNT AND CONTROL TO THE COMPLETE PRODUCT CODE / LABEL.

1. Isolate the supply before excavation, connection, insertion or service.
2. Confirm the exact fixture and matching mounting part before preparing the recess.
3. Set the sleeve or channel level and flush; provide a permanent free-draining base.
4. Keep every cable entry and field joint sealed with the specified IP-rated system.
5. Commission only after the mechanical seat, seal and drainage are complete.

DO NOT SUBSTITUTE THE BURIAL PART, LEAVE A CABLE JOINT IN STANDING WATER OR INSTALL BELOW GRADE.

ELA702 VERIFIED SOURCE DATA

FIXTURE	D55 x H65 mm
MOUNTING	D45 x H70 mm SLEEVE
RECESS	MATCH SLEEVE / FREE-DRAINING
INPUT / POWER	12V 24V / 3W
CCT	2700K/3000K/4000K
CRI / BEAM	Ra 80 / 12° 22° 28° 36° 50°
CONTROL	DALI Bluetooth DC0-10V ON/OFF
MATERIAL	304Stainless steel+6063#aluminum

Installation and commissioning must be performed by qualified technical personnel.

The D55 x H65 mm fixture shown above follows the ELA702 source sheet.

Use the exact product-specific mounting part: D45 x H70 mm BURIAL SLEEVE.

Coordinate recess, drainage, conduit, waterproof joints and finished grade before installation.

WARNING

- INSTALL THE FINISHED FACE FLUSH AND LEVEL; DO NOT LEAVE A TRIP EDGE.
- PROVIDE DRAINAGE; DO NOT PLACE THE CONNECTOR OR DRIVER IN STANDING WATER.
- ISOLATE POWER AND FOLLOW THE COMPLETE PRODUCT CODE / LABEL BEFORE CONNECTION.



CE IP FLUSH D DRAIN