

LED RECESSED DOWNLIGHT INSTALLATION GUIDE

Eurolumen


MODEL ELX101

1




CHECK COMPONENTS

2



CUT OPENING TO CONFIRMED SIZE

3



CONNECT MATCHED DRIVER

4



ALIGN CONCEALED RETAINERS

5




PUSH IN / LOCK RETAINERS

6




CHECK FLUSH FIT / POWER ON

WIRING DIAGRAM



MOUNTING DATA



INSTALLATION TYPE	RECESSED / CONCEALED PUSH-FIT / INDOOR, DRY LOCATION
PRODUCT SIZE	Ø63 x H92 mm

INPUT	220V AC VIA MATCHED DRIVER
POWER	6W / 8W



Installation must be performed under the guidance of qualified technical personnel.

Switch off and isolate the mains supply before installation or maintenance.

Confirm the selected driver and dimming control match the product label.

Retain this guide with the project handover and maintenance records.

WARNING

- Do not install while power is on.
- Keep insulation and combustible material clear of the luminaire and driver.
- Use only the matched driver and confirmed mounting dimensions.

CE

RoHS

